

# EL-6120 QUICK GUIDE

This guide briefly covers all of the functions of the EL-6120. For further details, refer to the Operation Manual.

## FUNCTIONS AND FEATURES

### TEL Mode (TEL1, TEL2, TEL3 Files):

TEL mode "items" consist of a character part for storage of names and addresses and a numerical part to store telephone numbers. Three files let you organize calls according to types of calls. (i.e., TEL1: business associates, TEL2: relatives, TEL3: private.)

### MEMO Mode (MEMO1, MEMO2 Files):

MEMO mode "items" consist of one character part for storage of memos. It is divided into two files for item organization. (i.e., MEMO1: appointments, MEMO2: notes.)

### CALC Mode:

In the CALC mode, your EL-6120 serves as a calculator.

### SECRET Function:


Items in TEL and MEMO files can be designated as "secret". These items require a password to be accessed.

### MEMORY CHECK Function:

The Memory Check tells you instantly how much storage space is left in the TEL and MEMO files, as well as how many items are stored in each file.

## FILE SELECTION

Press **MENU** to display the files in the following order:



- A new file is selected each time **MENU** is pressed.
- Press **SHIFT** **MENU** to select files in reverse order.

## TEL AND MEMO MODES

Example:  
TEL1


NAME	NUMBER
SMITH JOHN ACME	247-6100
JONES FRED GENERAL	613-2975
BROWN ED SHARP	533-7178
	364-3490

## MEMO1

MEMO
4/30 9:00 PLANNING MEETING
5/1 10:00 SOFTBALL

## Entering Items

1. Select the desired file.



2. Type up to 80 characters, using **↵** to separate lines, and press **ENT** to complete the NAME entry of a TEL item or the MEMO entry of a MEMO item.





3. Repeat the step 2 to store another MEMO item in the same file.

4. Type up to 80 characters, separating different phone numbers by pressing **↵**, and press **ENT** to complete the NUMBER entry of a TEL item.



5. Repeat the steps 2 and 4 to store another TEL item in the same file.

- Items are stored in MEMO files by the same method used to store NAME entries in TEL files.
- Items in both TEL and MEMO files are arranged alphanumerically according to the first characters of their first lines.



## Recalling Items

1. Select the desired file.

MENU  
SHIFT [A] TEL MEMO EDIT [M] E  
TEL 1  
NAME ?

Items can be recalled by either their first or second lines if the lines were separated by [J] during storage.

2. Press [1V] to recall the items in alphabetical order by the first lines. (Sequential searching)

[1V]  
SHIFT [A] TEL MEMO EDIT [M] E  
BROWN ED  
5 3 3 - 7 1 7 8

OR

Press [2V] to recall them by their second lines.

[2V]  
SHIFT [A] TEL MEMO EDIT [M] E  
BROWN ED  
SHARP

OR

Type the first character or group of characters (up to 10) of the first line of an item and press [1V]. (Direct searching)

SHIFT [A] TEL MEMO EDIT [M] E

BROWN

[1V]

BROWN ED  
5 3 3 - 7 1 7 8

OR

Type the first character or group of characters (up to 10) of the second line of an item and press [2V].

SHIFT [A] TEL MEMO EDIT [M] E

SHARP

[2V]

BROWN ED  
SHARP

3. Press [v] to display other lines of the TEL or MEMO item.  
Press [r] to display other lines of the NUMBER entry of the TEL item.

SHIFT [A] TEL MEMO EDIT [M] E

[r]

(2 times)

BROWN ED  
3 6 4 - 3 4 9 0

SHIFT [A] TEL MEMO EDIT [M] E

[v]

BROWN ED  
SHARP

SHIFT [A] TEL MEMO EDIT [M] E

[v]

5 3 3 - 7 1 7 8  
3 6 4 - 3 4 9 0

## Correcting Items

1. Select the desired file.

MENU  
SHIFT [A] TEL MEMO EDIT [M] E  
TEL 1  
NAME ?

2. Recall the desired item.

SHIFT [A] TEL MEMO EDIT [M] E  
SMITH  
[1V]  
SMITH JOHN  
2 4 7 - 6 1 0 0

3. Press [SHIFT] [EDIT] to activate the EDIT function.

SHIFT [A] TEL MEMO EDIT [M] E  
[SHIFT] [EDIT]  
SMITH JOHN,  
ACME

4. Press [v] and [r] to move the cursor to the mistake.

SHIFT [A] TEL MEMO EDIT [M] E  
[r] (7 times)  
SMITH JOHN,  
ACME

5. Use [BS] to make the desired correction or enter the correct characters over the incorrect ones.

SHIFT [A] TEL MEMO EDIT [M] E  
EA  
SMITH JEAN,  
ACME

6. Repeat the steps 4 and 5 for other corrections.

SHIFT [A] TEL MEMO EDIT [M] E  
[v] [r]  
(2 times) R  
SMITH JEAN,  
ACRE

7. Press [ENT].

SHIFT [A] TEL MEMO EDIT [M] E  
[ENT]  
TEL 1  
NAME ?

## Deleting Items

1. Select the desired file.

SHIFT [A] TEL MEMO EDIT [M] E  
MENU  
TEL 1  
NAME ?

2. Recall the desired item.

SHIFT [A] TEL MEMO EDIT [M] E  
S [1V]  
SMITH JEAN  
2 4 7 - 6 1 0 0

3. Activate the EDIT function and press [C-CE].

SHIFT [A] TEL MEMO EDIT [M] E  
[SHIFT] [EDIT]  
[C-CE]  
SMITH JEAN  
DELETE ? Y/N

(TCADH1721CCZZ)

3. Press **Y** to delete the item.

SHIFT **A** TEL MEMO EDIT **M**E

**Y**

TEL 1  
NAME ?

- Press **N** to retain the item.

### Clearing a File

1. Select the desired file.
2. Hold down **BS**, press the reset switch.
3. Press **Y** to delete the entire contents of the file.

- Press **N** to retain the file.

### Clearing the Memory

1. Press the reset switch.
  2. Press **Y** to completely clear the memory, including the calculator memory.
- Press **N** to retain the contents of the memory.

### SECRET FUNCTION

Items in TEL and MEMO files can be designated as secret by inserting an asterisk(\*) in front of them. These items cannot be recalled unless a password is entered.

### Selecting a Password

1. Select a TEL or MEMO file.

SHIFT **A** TEL MEMO EDIT **M**E

**MENU**

MEMO 1  
?

2. Press **SHIFT SECRET**.

SHIFT **A** TEL MEMO EDIT **M**E

**SHIFT SECRET**

PASSWORD SET  
?

3. Type a password of six characters or less and press **ENT**.

SHIFT **A** TEL MEMO EDIT **M**E

ABCDEF

**ENT**

PASSWORD  
[ABCDEF] SET

4. Press **C-CE** to activate the SECRET function.

SHIFT **A** TEL MEMO EDIT **M**E

**C-CE**

MEMO 1  
?

### Designating Items as Secret

Items are designated as secret by inserting an asterisk (\*) in front of them.

### To designate an item already stored as secret

1. Select the desired file.

SHIFT **A** TEL MEMO EDIT **M**E

**MENU**

MEMO 1  
?

2. Recall the desired item.

SHIFT **A** TEL MEMO EDIT **M**E

**ALPHA** 4/30

**IV**

4 / 30 9 : 00  
PLANNING MEE

3. Press **SHIFT EDIT** to activate the EDIT function.

SHIFT **A** TEL MEMO EDIT **M**E

**SHIFT EDIT**

4 / 30 9 : 00  
PLANNING MEE

4. Press **SHIFT MARK\*** to insert an asterisk at the beginning of the item.

SHIFT **A** TEL MEMO EDIT **M**E

**SHIFT MARK\***

\* 4 / 30 9 : 00  
PLANNING MEE

5. Press **ENT**.

SHIFT **A** TEL MEMO EDIT **M**E

**ENT**

MEMO 1  
?

### To designate an item as secret during storage

1. Select the desired file.
2. Press **SHIFT MARK\***.
3. Store the item as you would a regular item.

### Recalling Secret Items

(Cancelling the SECRET Function)

1. Select the desired file.

SHIFT **A** TEL MEMO EDIT **M**E

**MENU**

MEMO 1  
?

2. Enter the password and press **SHIFT SECRET** to cancel the SECRET function.

SHIFT **A** TEL MEMO EDIT **M**E

ABCDEF

**SHIFT SECRET**

MEMO 1  
?

3. Recall the desired item.

SHIFT [A] TEL MEMO EDIT [M] E

1V

\* 4 / 3 0 9 : 0 0  
PLANNING MEE

4. When finished with secret items, press SHIFT SECRET to reactivate the SECRET function.

- The SECRET function will be reactivated automatically when the power is turned off manually or automatically.

### Changing the Password

1. Type the current password and press SHIFT SECRET to cancel the SECRET function.

SHIFT [A] TEL MEMO EDIT [M] E

ABCDEF  
SHIFT SECRET

MEMO 1  
?

2. Type the current password again and press SHIFT SECRET again.

SHIFT [A] TEL MEMO EDIT [M] E

ABCDEF  
SHIFT SECRET

PASSWORD SET  
?

3. Type the new password and press ENT to activate the SECRET function.

SHIFT [A] TEL MEMO EDIT [M] E

UNCLE  
ENT

PASSWORD  
[UNCLE] SET

### If You Forget the Password

- Hold down C-CE and press the reset switch on the back of the calculator.
- Press Y to delete the current password.
  - All secret items will be deleted along with the password.
  - Press N to retain the password and secret items.

### MEMORY CHECK FUNCTION

1. Press SHIFT M to display the amount of storage space left in the TEL and MEMO files.

SHIFT [A] TEL MEMO EDIT [M] E

SHIFT M

1744 CHARA  
REMAINING

2. Press M again to display the number of items stored in each of the three TEL files.

SHIFT [A] TEL MEMO EDIT [M] E

M

T 1 : 0 0 2 2 : 0 0 0  
3 : 0 0 0

3. Press M a third time to display the number of items in each of the two MEMO files.

SHIFT [A] TEL MEMO EDIT [M] E

M

M 1 : 0 0 2  
2 : 0 0 0

### CALC MODE

1. Select the CALC mode.

SHIFT [A] TEL MEMO EDIT [M] E

MENU

0.

- Before performing a calculation, press C-CE.

SHIFT [A] TEL MEMO EDIT [M] E

C-CE

123 +

456 =

579.

**Note:** The contents of the calculator, telephone and memo memories are retained even after the power is turned off either manually or automatically. All data in the memory will be lost, however, if the main power batteries and the memory backup battery are all removed at the same time, or if the memory backup battery is removed when the main batteries are worn. The memory backup battery should be replaced at least every 5 years of interval.